



جدول مشخصات درایو ماژولار MV :

Bypass Cabin (optional)		Weight	D	W1	H	EBD Model	Power	Voltage
Weight	W2							
Kg	mm	kg	mm	mm	mm		KW	KV
700	1030	1500	1200	2800	2100	EB01DMZ016--	160	3.3
700	1030	1500	1200	2800	2100	EB01DMZ020--	200	
700	1030	1800	1200	2800	2100	EB01DMZ025--	250	
700	1030	1800	1200	2800	2100	EB01DMZ032--	315	
700	1030	2600	1200	2800	2100	EB01DMZ036--	355	
700	1030	2600	1200	2800	2100	EB01DMZ040--	400	
700	1030	2600	1200	2800	2100	EB01DMZ045--	450	
700	1030	2600	1200	2800	2100	EB01DMZ050--	500	
900	1030	3300	1200	3740	2400	EB01DMZ053--	530	
900	1030	3300	1200	3740	2400	EB01DMZ063--	630	
900	1030	3300	1200	3740	2400	EB01DMZ071--	710	
900	1030	3300	1200	3740	2400	EB01DMZ080--	800	
900	1030	4000	1200	3740	2400	EB01DMZ090--	900	
900	1030	4000	1200	3740	2400	EB01DMZ100--	1000	
900	1030	4000	1200	3740	2400	EB01DMZ112--	1120	
900	1030	4800	1400	4300	2400	EB01DMZ125--	1250	
900	1030	4800	1400	4300	2400	EB01DMZ135--	1350	
800	1030	9500	1400	4850	2700	EB01DMZ200--	2000	
800	1030	10500	1400	5450	2700	EB01DMZ256--	2560	
800	1030	11500	1400	6200	2782	EB01DMZ311--	3110	
800	1030	12000	1400	6200	2782	EB01DMZ384--	3840	
700	1030	1600	1200	3100	2100	EB01DMA016--	160	4.16
700	1030	1600	1200	3100	2100	EB01DMA020--	200	
700	1030	1600	1200	3100	2100	EB01DMA025--	250	
700	1030	1900	1200	3100	2100	EB01DMA032--	315	

..... این دستورالعمل جزء اسناد و مدارک شرکت اطمینان بخش می باشد ... صفحه 1 از 5 هرگونه کپی برداری بدون مجوز کتبی ممنوع می باشد.....



700	1030	1900	1200	3100	2100	EB01DMA036--	355	
700	1030	1900	1200	3100	2100	EB01DMA040--	400	
700	1030	3000	1200	3100	2100	EB01DMA045--	450	
Bypass Cabin (optional)		Weight	D	W1	H	EBD Model	Power	Voltage
Weight	W2							
Kg	mm	kg	mm	mm	mm		KW	KV
700	1030	3000	1200	3100	2100	EB01DMA050--	500	4.16
700	1030	3000	1200	3100	2100	EB01DMA056--	560	
700	1030	3000	1200	3100	2100	EB01DMA063--	630	
900	1030	3800	1200	3800	2400	EB01DMA071--	710	
900	1030	3800	1200	3800	2400	EB01DMA080--	800	
900	1030	3800	1200	3800	2400	EB01DMA090--	900	
900	1030	3800	1200	3800	2400	EB01DMA100--	1000	
900	1030	4300	1200	4200	2400	EB01DMA112--	1120	
900	1030	4300	1200	4200	2400	EB01DMA125--	1250	
900	1030	4300	1200	4200	2400	EB01DMA135--	1350	
900	1030	5100	1400	4200	2400	EB01DMA150--	1500	
900	1030	5100	1400	4200	2400	EB01DMA180--	1800	
800	1030	9500	1400	5400	2700	EB01DMA252--	2520	
800	1030	10400	1400	6000	2700	EB01DMA323--	3230	
800	1030	11600	1400	6900	2782	EB01DMA392--	3920	
800	1030	13500	1400	6900	2782	EB01DMA484--	4840	
700	1030	2500	1200	3720	2100	EB01DMB028--	280	6
700	1030	2500	1200	3720	2100	EB01DMB032--	315	
700	1030	2500	1200	3720	2100	EB01DMB036--	355	
700	1030	3100	1200	3720	2100	EB01DMB040--	400	
700	1030	3100	1200	3720	2100	EB01DMB045--	450	
700	1030	3100	1200	3720	2100	EB01DMB050--	500	
700	1030	3100	1200	3720	2100	EB01DMB056--	560	
700	1030	3800	1200	3820	2100	EB01DMB063--	630	
700	1030	3800	1200	3820	2100	EB01DMB071--	710	
700	1030	4600	1200	3820	2100	EB01DMB080--	800	
700	1030	4600	1200	3820	2100	EB01DMB090--	900	
700	1030	4600	1200	3820	2100	EB01DMB100--	1000	
700	1030	4600	1200	4070	2400	EB01DMB112--	1120	
800	1030	5900	1200	4070	2400	EB01DMB125--	1250	
800	1030	5900	1200	4070	2400	EB01DMB140--	1400	
800	1030	7400	1200	4070	2400	EB01DMB160--	1600	
800	1030	7400	1400	4070	2400	EB01DMB180--	1800	
800	1030	7400	1400	4070	2400	EB01DMB200--	2000	
800	1030	7800	1400	4070	2400	EB01DMB224--	2240	

..... این دستورالعمل جزء اسناد و مدارک شرکت اطمینان بخش می باشد ... صفحه 2 از 5 هرگونه کپی برداری بدون مجوز کتبی ممنوع می باشد.....



800	1030	7800	1400	4070	2400	EB01DMB250--	2500	6.6
950	1030	10500	1450	7180	2740	EB01DMB364--	3640	
1050	1030	12000	1500	8000	2900	EB01DMB466--	4660	
1050	1030	13200	1600	8000	2900	EB01DMB565--	5650	
1050	1030	14000	1600	8000	2900	EB01DMB698--	6980	
700	1030	3200	1200	3800	2100	EB01DMC025--	250	
700	1030	3200	1200	3800	2100	EB01DMC032--	315	
Bypass Cabin (optional)		Weight	D	W1	H	EBD Model	Power	Voltage
Weight	W2							
Kg	mm	kg	mm	mm	mm		KW	KV
700	1030	3200	1200	3800	2100	EB01DMC036--	355	6.6
700	1030	3200	1200	3800	2100	EB01DMC040--	400	
700	1030	3200	1200	3800	2100	EB01DMC045--	450	
700	1030	3800	1200	3800	2100	EB01DMC050--	500	
700	1030	3800	1200	3800	2100	EB01DMC056--	560	
700	1030	3800	1200	3800	2100	EB01DMC063--	630	
700	1030	5700	1200	3800	2100	EB01DMC071--	710	
700	1030	5700	1200	3800	2100	EB01DMC080--	800	
700	1030	5700	1200	3800	2100	EB01DMC090--	900	
700	1030	5700	1200	3800	2100	EB01DMC100--	1000	
900	1030	6800	1200	4430	2400	EB01DMC112--	1120	
900	1030	6800	1200	4430	2400	EB01DMC125--	1250	
900	1030	6800	1200	4430	2400	EB01DMC135--	1350	
900	1030	6800	1200	4430	2400	EB01DMC150--	1500	
900	1030	6800	1200	4430	2400	EB01DMC180--	1800	
900	1030	8300	1200	4800	2400	EB01DMC200--	2000	
900	1030	8300	1200	4800	2400	EB01DMC224--	2240	
900	1030	8300	1200	4800	2400	EB01DMC240--	2400	
900	1030	9400	1400	5100	2400	EB01DMC250--	2500	
900	1030	9400	1400	5100	2400	EB01DMC290--	2900	
1050	1030	9800	1400	6600	2700	EB01DMC400--	4000	
1050	1030	10700	1400	7800	2700	EB01DMC512--	5120	
1050	1030	11300	1400	7800	2782	EB01DMC622--	6220	
1050	1030	12500	1400	7800	2782	EB01DMC768--	7680	
700	1030	3800	1200	4200	2100	EB01DME028--	280	10
700	1030	3800	1200	4200	2100	EB01DME032--	315	
700	1030	3800	1200	4200	2100	EB01DME036--	355	
700	1030	3800	1200	4200	2100	EB01DME040--	400	
700	1030	3800	1200	4200	2100	EB01DME045--	450	
700	1030	3800	1200	4200	2100	EB01DME056--	560	
700	1030	3800	1200	4200	2100	EB01DME063--	630	

..... این دستورالعمل جزء اسناد و مدارک شرکت اطمینان بخش می باشد ... صفحه 3 از 5 هرگونه کپی برداری بدون مجوز کتبی ممنوع می باشد.....



700	1030	5100	1200	4200	2100	EB01DME071--	710	
700	1030	5100	1200	4200	2400	EB01DME080--	800	
700	1030	5100	1200	4200	2400	EB01DME090--	900	
700	1030	5900	1200	4920	2400	EB01DME100--	1000	
700	1030	5900	1200	4920	2400	EB01DME112--	1120	
700	1030	5900	1200	4920	2400	EB01DME125--	1250	
700	1030	6500	1400	4920	2400	EB01DME140--	1400	
700	1030	6500	1400	4920	2400	EB01DME160--	1600	
700	1030	6500	1400	4920	2400	EB01DME180--	1800	
800	1030	8200	1400	5640	2400	EB01DME200--	2000	
800	1030	8200	1400	5640	2400	EB01DME224--	2240	
Bypass Cabin (optional)		Weight	D	W1	H	EBD Model	Power	Voltage
Weight	W2							
Kg	mm	kg	mm	mm	mm		KW	KV
800	1030	8200	1400	5640	2400	EB01DME250--	2500	10
800	1030	9700	1400	5640	2400	EB01DME280--	2800	
800	1030	9700	1400	5640	2400	EB01DME315--	3150	
800	1030	10800	1400	5640	2400	EB01DME355--	3550	
800	1030	10800	1400	5640	2400	EB01DME400--	4000	
1000	1030	13500	1500	9280	2740	EB01DME607--	6070	
1050	1030	14000	1550	10400	2900	EB01DME776--	7760	
1050	1030	15600	1600	11400	2900	EB01DME942--	9420	
1050	1030	17300	1600	11400	2900	EB01DME1164--	11640	
700	1030	5000	1200	5100	2100	EB01DMF032--	315	11
700	1030	5000	1200	5100	2100	EB01DMF035--	355	
700	1030	5000	1200	5100	2100	EB01DMF045--	450	
700	1030	5000	1200	5100	2100	EB01DMF053--	530	
700	1030	5000	1200	5100	2100	EB01DMF056--	560	
700	1030	5000	1200	5100	2100	EB01DMF063--	630	
700	1030	6100	1200	5100	2100	EB01DMF071--	710	
900	1030	6100	1200	5400	2400	EB01DMF080--	800	
900	1030	6100	1200	5400	2400	EB01DMF090--	900	
900	1030	6100	1200	5400	2400	EB01DMF100--	1000	
900	1030	7500	1200	5400	2400	EB01DMF112--	1120	
900	1030	7500	1200	5400	2400	EB01DMF125--	1250	
900	1030	7500	1200	5400	2400	EB01DMF135--	1350	
900	1030	7500	1200	5400	2400	EB01DMF150--	1500	
900	1030	7500	1200	5400	2400	EB01DMF180--	1800	
900	1030	9500	1400	6200	2400	EB01DMF200--	2000	
900	1030	9500	1400	6200	2400	EB01DMF240--	2400	
900	1030	9500	1400	6200	2400	EB01DMF280--	2800	
900	1030	9500	1400	6200	2400	EB01DMF300--	3000	

..... این دستورالعمل جزء اسناد و مدارک شرکت اطمینان بخش می باشد ... صفحه 4 از 5 هرگونه کپی برداری بدون مجوز کتبی ممنوع می باشد.....

1000	1030	12000	1450	6500	2500	EB01DMF315--	3150
1000	1030	12000	1450	6500	2500	EB01DMF340--	3400
1000	1030	12000	1450	6500	2500	EB01DMF380--	3800
1000	1030	12000	1450	6500	2500	EB01DMF400--	4000
1000	1030	13100	1450	6500	2500	EB01DMF420--	4200
1000	1030	13100	1450	6500	2500	EB01DMF460--	4600
1050	1030	13900	1450	9900	2850	EB01DMF668--	6680
1050	1030	15000	1550	11900	2900	EB01DMF854--	8540
1050	1030	16800	1600	12500	2900	EB01DMF1036--	10360
1050	1030	19000	1600	12500	2900	EB01DMF1280--	12800